



Gearbox Technical Specifications

Unit	Motor Frame Size	Flange Dimensions			Speed Ratio from 7.5:1 to 100:1										
		C	I	E	7,5	10	15	20	25	30	40	50	60	80	100
D Input Motor Shaft Sizes (mm)															
CHM 025	56B14	50	65	80	9	9	9	9	9	9	9	9	9		
CHM 030	63B5	95	115	140	11	11	11	11	11	11	11	11			
	63B14	60	75	90											
	56B5	80	100	120	9	9	9	9	9	9	9	9	9	9	
CHM 040	56B14	50	65	80											
	71B5	110	130	160	14	14	14	14	14	14					
	71B14	70	85	105											
	63B5	95	115	140	11	11	11	11	11	11	11	11	11	11	11
CHM 050	63B14	60	75	90											
	56B5	80	100	120								9	9	9	9
	80B5	130	165	200	19	19	19	19	19	19					
	80B14	80	100	120											
CHM 063	71B5	110	130	160	14	14	14	14	14	14	14	14	14	14	14
	71B14	70	85	105											
	63B5	95	115	140							11	11	11	11	11
	90B5	130	165	200	24	24	24	24	24	24					
	90B14	95	115	140											
	80B5	130	165	200	19	19	19	19	19	19	19	19	19	19	
CHM 075	80B14	80	100	120											
	71B5	110	130	160								14	14	14	14
	100/112B5	180	215	250	28	28	28								
	100/112B14	110	130	160											
	90B5	130	165	200	24	24	24	24	24	24	24	24			
	90B14	95	115	140											
CHM 090	80B5	130	165	200											
	80B14	80	100	120								19	19	19	19
	100/112B5	180	215	250	28	28	28	28	28	28					
	100/112B14	110	130	160											
	90B5	130	165	200	24	24	24	24	24	24	24	24	24		
CHM 110	90B14	95	115	140											
	80B5	130	165	200											
	80B14	80	100	120											
	132B5	230	265	300	38	38	38	38							
	100/112B5	180	215	250	28	28	28	28	28	28	28	28	28		
CHM 130	100/112B14	110	130	160											
	90B5	130	165	200											
	90B14	95	115	140										19	19

If a dimension is critical to your application please contact our sales department for confirmation.
Please note : errors and omissions excepted.